

HDMI-X42

RS-232 Protocol

* RS-232 transmission format:

Baud Rate : 9600 bps

Data Bit : 8 bits

Parity : None

Stop Bit : 1 bit

Command:

* The command will be executed after ASCII character "CR" input

* After ASCII character "CR" is entered, The unit will reply "OK" if the command is legal

* If the command is illegal, The unit will reply "NG"

Command Code	Comment
P0	POWER OFF
P1	POWER ON
A1	OUTPUT A select INPUT 1
A2	OUTPUT A select INPUT 2
A3	OUTPUT A select INPUT 3
A4	OUTPUT A select INPUT 4
B1	OUTPUT B select INPUT 1
B2	OUTPUT B select INPUT 2
B3	OUTPUT B select INPUT 3
B4	OUTPUT B select INPUT 4