

HDMI-8I

RS-232 Protocol

* RS-232 transmission format:

Baud Rate : 9600 bps

Data Bit : 8 bits

Parity : None

Stop Bit : 1 bit

Command:

- * A command is combined with a word plus a digit
- * This combination command code has to be separated by ASCII character SPACE
- * The command will be executed after ASCII character "CR" input
- * After ASCII character "CR" is entered, The unit will reply "OK" if the command is legal
- * If the command is illegal, The unit will reply "NG"

Command Code	Comment
"PORT"+ SPACE+"1"+CR	PORT 1 ON
"PORT"+ SPACE+"2"+CR	PORT 2 ON
"PORT"+ SPACE+"3"+CR	PORT 3 ON
"PORT"+ SPACE+"4"+CR	PORT 4 ON
"PORT"+ SPACE+"5"+CR	PORT 5 ON
"PORT"+ SPACE+"6"+CR	PORT 6 ON
"PORT"+ SPACE+"7"+CR	PORT 7 ON
"PORT"+ SPACE+"8"+CR	PORT 8 ON
"SIGNAL"+SPACE+"1"+CR	ENABLE SIGNAL ENHANCE
"SIGNAL"+SPACE+"0"+CR	DISABLE SIGNAL ENHANCE
"POWER"+ SPACE+"1"+CR	POWER ON
"POWER"+ SPACE+"0"+CR	POWER OFF